在集中监看软件中如何录像移动侦测

1. 首先进入摄像机的 WEB 管理界面,进入"设置"选项,如下图:



在下图中请按正确序号操作,如下图标示:
 (1. 进入"高级设置", 2. 进入"报警事件"。)

新						
(Shasee) #	ALARM EVENT					
·····································	Embedded Motion Detection Setting					
► ■Basic Configuration						
►Advance Configuration						
-						
- NEW LOGO						
- ●FTP	and the second sec					
- ●SMTP						
- ALARM EVENT						
- ●PTZ						
- CHANGE PASSWOD						
- ADMINISTRATOR						
- ODNS						
- MAINTENANCE						
	Set Motion Detect Region:	Begin 0 Edit Region Or Remove Region End Edit				
Return	Sensitivity	50				
	Motion Detection Enabled	Yes 🖲 No 🔘				
	Embedded Motion Detection Event					
	Send E-mail with a JPEG or send to FTP with *.AV	e-Mail JPEG 🔻				
	GPIO Alarm					
	GPIO(Input) Alarm Level Alarm Event	GPIO(Output) GPIO Status				
	GPIO1 No alarm	GPIO3 O High O Low				
	GPIO2 No alarm 👻 No alarm 👻	GPIO4 O High C Low				
	Save Reset					

注意:设置"红色框所标示区域"

1. 请单击"开始"按钮,然后设置"0"号移动侦测区域,单击鼠标左键在图像区域内划出一个区域(左上角 会显示当前区域号),如果你需要设置更多的区域,请选择"1"和其它的相关数值,最大16个区域,操作如 同上面。每个区域设置好后,请单击"结束编辑"结束,最后单击"保存"保存上述所操作。(如果移动侦测 区域设置好后,你将会看到在各个区域内如果有图像移动,这个区域边框将红灰色交替显示。) 3. 在集中监控软件中相关设置(首先必须设置 WEB 界面所指示操作)

第1页. 请进入当前网络摄像机的"设备设置"中,在这里面,请选择"报警"页面,在报警页面请选择"启 用报警"在时间部署框内,请添加一个时间段,请看第2页。

第2页. 在此页面中,请选择你所要监控的布防时间段,同时引发的触发条件是"移动侦测",请务必选中它, 在报警动作中请"选择"并进入第3页。

👍 M Serials Options 第1贝	Modify the alarming time section 第2贝 🔲
Name: IP Camera	Week: <u>Select All</u> <u>Unselect All</u>
Connect General Equipment Options Alarming Record Others	🗹 Monday 📝 Tuesday 📝 Wednesday 📝 Thursday
Enable Alarm	🗹 Friday 🔽 Saturday 🔽 Sunday
Alarm Group:	Time:
Deployment Time:	Start Time: 0:00:00
Week Time Trigger Action	End Time: 23:59:59
All Time 0:00:00 - 23:59:59 Motion Detec Sound,V	Alarming duration (seconds):
	30 至
	Trigger: <u>Select All</u> <u>Unselect All</u>
	Motion Detection
	GPI 1 GPI 2 GPI 3 GPI 4
Add Modify Delete Clear	🖸 GPI 5 🗌 GPI 6 🔲 GPI 7 🔲 GPI 8
	Action: Select
Apply to all equipment	Sound
Apply to the same group	Video Record
<u>o</u> k	<u>Q</u> K <u>C</u> ancel

第3页. 在此页面中你将会看到很多的触发条件,选择"声音"当报警触发时会在本地服务器发出报警声音,"录像"选项则触发报警时将自动录像并保存。

👙 Add Alarm Action		第3页	
Sound	<u> </u>	Video Record	
🗹 📴 Video Record		Recording Video on alarming.	
🗆 🖻 Picture			
🗆 😨 Flow Statistics			
🗆 🐳 Siren	E		
🗆 🖾 E-mail			
🗆 👥 FTP			Equipment List
🗆 🧇 Telephone			Operator Manage (M)
🗆 🚍 SMS Modem			Log management
🗆 🗟 Skype			History Records Web Publisher Automatic fil IP cam Searcher
	•		Population Flow Statistics
			About
			Help
日常录像及报警录像,请查看"历史记录"。			
其它的请参考帮助文档。=>			New version check